


NASA TECH BRIEF



NASA Tech Briefs are issued to summarize specific innovations derived from the U. S. space program and to encourage their commercial application. Copies are available to the public from the Clearinghouse for Federal Scientific and Technical Information, Springfield, Virginia 22151.

Substituting Transistor for Diode Improves Rectifying Means



The problem:

In rectifying an alternating current, prior art has used silicon diodes which have exhibited a forward voltage drop and relatively slow turnoff time. The former disadvantage is important when the forward voltage drop is a significant proportion of the total load voltage. The latter disadvantage restricts the repetition rate of the alternating voltage to a low value.

The solution:

An unusual transistor connection that substitutes for the diode and allows significantly higher repetition rates without increasing power loss.

How it's done:

The improvement is made by substituting circuit A-B-C in the right figure for circuit A-B-C in the left figure. In operation, T_1 is pulsed on. This creates a magnetic field in the transformer and supplies the load current. Transformer action also reverse biases T_2 at this time. As T_1 turns off, the magnetic field in the transformer collapses and turns on T_2 . The current from the collapsing field flows into the collector,

which is the inverted connection of T_2 that is employed to get good voltage breakdown characteristics for T_2 when T_1 is on. Saturation voltage is very low in this configuration and results in an equivalent diode of very low forward voltage drop.

Notes:

1. Operation speed is improved by a factor of 10 or more when a given diode is replaced by this transistor circuit.
2. The circuit on the left, when converting 28 volts to a load voltage of 4 volts, operated at less than 69% efficiency. When it was replaced with the circuit A-B-C in the right figure, an efficiency of 80% was achieved.
3. This circuit should be beneficial for use in power converters where the load voltage is low.
4. Inquiries concerning this invention may be directed to:

Technology Utilization Officer
Goddard Space Flight Center
Greenbelt, Maryland 20771
Reference: B66-10295

(continued overleaf)

Patent status:

Inquiries about obtaining rights for the commercial use of this invention may be made to NASA, Code GP, Washington, D.C. 20546.

Source: Ronald M. Muller
(GSFC-474)